



SOT-23 Plastic-Encapsulate Transistors

S9018Z-J8

S9018Z TRANSISTOR (NPN)

FEATURES

- AM/FM Amplifier, Local Oscillator of FM/VHF Tuner
- High Current Gain Bandwidth Product $f_T=1.1$ GHz (Typ)

MARKING: J8

SOT-23

1. BASE
2. Emitter
3. Collector



MAXIMUM RATINGS ($T_A=25^\circ\text{C}$ unless otherwise noted)

Symbol	Parameter	Value	Units
V_{CBO}	Collector-Base Voltage	30	V
V_{CEO}	Collector-Emitter Voltage	18	V
V_{EBO}	Emitter-Base Voltage	5	V
I_C	Collector Current -Continuous	50	mA
P_c	Collector Power Dissipation	200	mW
T_j	Junction Temperature	150	°C
T_{stg}	Storage Temperature	-55-150	°C

ELECTRICAL CHARACTERISTICS (Tamb=25°C unless otherwise specified)

Parameter	Symbol	Test conditions	MIN	TYP	MAX	UNIT
Collector-base breakdown voltage	$V_{(BR)CBO}$	$I_C= 100\mu\text{A}, I_E=0$	30			V
Collector-emitter breakdown voltage	$V_{(BR)CEO}$	$I_C= 1\text{mA}, I_B=0$	18			V
Emitter-base breakdown voltage	$V_{(BR)EBO}$	$I_E=100\mu\text{A}, I_C=0$	5			V
Collector cut-off current	I_{CBO}	$V_{CB}=20\text{V}, I_E=0$			0.1	μA
Collector cut-off current	I_{CEO}	$V_{CE}=12\text{V}, I_B=0$			1	μA
Emitter cut-off current	I_{EBO}	$V_{EB}= 3\text{V}, I_C=0$			0.1	μA
DC current gain	$h_{FE(1)}$	$V_{CE}=5\text{V}, I_C= 1\text{mA}$	70		300	
Collector-emitter saturation voltage	$V_{CE(\text{sat})}$	$I_C=10\text{mA}, I_B= 1\text{mA}$			0.5	V
Base-emitter saturation voltage	$V_{BE(\text{sat})}$	$I_C=10\text{mA}, I_B= 1\text{mA}$			1.4	V
Transition frequency	f_T	$V_{CE}=5\text{V}, I_C= 5\text{mA}$ $f=400\text{MHz}$	600			MHz

CLASSIFICATION OF h_{FE}

Rank	H	
Range	100-200	